

B R O A D W A V E T E C H N O L O G I E S I N C .

MODEL 852 - 879 - FM3
IMPEDANCE MATCHING PAD

Frequency Range: DC - 3000 MHz

Impedance: 75 Ohms nominal (Male side)
50 Ohms nominal (Female side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.45:1 maximum

Input Power: 1 Watt average

Connectors: Type F Male / N Female

Outline Drawing: MED - 0453

| ECF # | Date | Rev. |
|-------|---------|------|
| Issue | 9/24/08 | 0 |
| | | |
| | | |
| | | |

Approved By: _____