

Approved Internet/Email Copy

B R O A D W A V E T E C H N O L O G I E S I N C .

**MODEL 854 – 874 – FM2
IMPEDANCE MATCHING PAD**

Frequency Range: 1 - 2000 MHz

Impedance: 50 Ohms nominal (Female side)
 75 Ohms nominal (Male side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.50:1 maximum

Input Power: 1 Watt average

Connectors: BNC Male / Female

Outline Drawing: MED - 0103

ECF #	Date	Rev.
Issue	08/31/06	0

Approved By: _____