

---

MODEL 854 - 879 – FM2

IMPEDANCE MATCHING PAD

---

**Frequency Range:** DC - 2 GHz

**Impedance:** 50 Ohms nominal ( BNC Female side )  
75 Ohms nominal ( F Male side )

**Insertion Loss:** 5.7 dB nominal

**VSWR:** 1.40:1 maximum

**Input Power:** 1 Watt average

**Connectors:** BNC Female / F male

**Outline Drawing:** MED-0302

ECF #	Date	Rev.
Issue	2/24/11	0

Approved By: \_\_\_\_\_