

B R O A D W A V E T E C H N O L O G I E S I N C .

---

MODEL 854 - 879 - MF2  
IMPEDANCE MATCHING PAD

---

Frequency Range: DC - 2 GHz

Impedance: 50 Ohms nominal ( BNC Male side )  
75 Ohms nominal ( F Female side )

Insertion Loss: 5.7 dB nominal

VSWR: 1.40:1 maximum

Input Power: 1 Watt average

Connectors: BNC Male / F Female

Outline Drawing: MED-0811

ECF #	Date	Rev.
Issue	2/17/04	0
0766	1/29/09	A

Approved By: \_\_\_\_\_