
MODEL 851 - 872 – FM2
IMPEDANCE MATCHING PAD

Frequency Range: DC - 2 GHz

Impedance: 50 Ohms nominal (Female side)
75 Ohms nominal (Male side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.4:1 maximum

Input Power: 1 Watt average

Connectors: SMA Female / N Male

Outline Drawing: MED - 0710

ECF #	Date	Rev.
Issue	2/9/07	0

Approved By: _____