

---

MODEL 851- 874- FM4  
IMPEDANCE MATCHING PAD

---

**Frequency Range:** DC - 4 GHz

**Impedance:** 50 Ohms nominal ( Female side )  
75 Ohms nominal ( Male side )

**Insertion Loss:** 5.7 dB nominal

**VSWR:** 1.45:1 maximum

**Input Power:** 1 Watt average

**Connectors:** SMA Female / BNC Male

**Outline Drawing:** MED - 0807

ECF #	Date	Rev.
Issue	6/7/2011	0

Approved By: \_\_\_\_\_