

**MODEL 854 - 874 - MF4**  
**IMPEDANCE MATCHING PAD**

---

**Frequency Range:** DC - 4 GHz

**Impedance:** 50 Ohms nominal ( Male side )  
75 Ohms nominal ( Female side )

**Insertion Loss:** 5.7 dB nominal

**VSWR:** 1.50:1 maximum

**Input Power:** 1 Watt average

**Connectors:** BNC Male / Female

**Outline Drawing:** MED - 0947

<b>ECF #</b>	<b>Date</b>	<b>Rev.</b>
Issue	07/27/12	0
2132	11/02/23	A

**Approved By:** Approved Internet/Email Copy