

MODEL 854 - 879 – FM3
IMPEDANCE MATCHING PAD

Frequency Range: DC - 3 GHz

Impedance: 50 Ohms nominal (BNC Female side)
75 Ohms nominal (F Male side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.50:1 maximum

Input Power: 1 Watt average

Connectors: BNC Female / F male

Outline Drawing: MED-0302

ECF #	Date	Rev.
Issue	01/30/12	0

Approved By: _____