
MODEL 854 - 894 - MF0
IMPEDANCE MATCHING PAD

Frequency Range: DC - 50 MHz

Impedance: 50 Ω nominal (Male side)
1000 Ω nominal (Female side)

Insertion Loss: 27 dB nominal

VSWR: 1.25:1 maximum

Input Power: 1 Watt average

Connectors: BNC Male / Female

Outline Drawing: MED - 0947

ECF #	Date	Rev.
Issue	07/20/06	0
1120	05/29/13	A
2065	10/25/21	B
2102	07/06/22	C

Approved By: _____