

---

**MODEL 894 - 052 - IMP**  
**IMPEDANCE MATCHING PAD**

---

**Frequency Range:** DC - 1 GHz

**Impedance:** 50 Ohms nominal ( Female side )  
93 Ohms nominal ( Male side )

**Insertion Loss:** 7.3 dB nominal

**VSWR:** 1.40:1 maximum

**Input Power:** 1 Watt average

**Connectors:** BNC Male / Female

**Outline Drawing:** MED - 0115

ECF #	Date	Rev.
Issue	5/11/16	0

Approved By: \_\_\_\_\_